



DES CRIP TION



The Baby Color Q70 IR is a compact, bright color-changing fixture controllable with a new infra-red remote controller. Its output is comparable with larger fixtures and can produce a wide range of colors, including shades of pastel.

This fixture has a 16° beam angle, and it has an included diffuser that widens the beam angle to 25°. It features a dimmer, strobe, macro effects, and audio control chases via display.

Features.




IR REMOTE CONTROL

The Baby Color Q70 IR comes with an infra-red remote controller that can set lighting commands. The controller can be used with or without the diffusion cover, as long as it is facingthe front LEDs.



COMPACT

This compact, powerful fixture is just five pounds, making it ideal for productions, weddings,banquets, conference rooms, and more.



RGBW COLOR-MIXING

This unit is built with seven 10W RGBW LEDs that allow for color-mixing with Red, Green, Blueand Cool White. Whether you're looking to produce vibrant and dynamic hues or delicate andintricate pastel luminations.

Specifications.

Mechanical Specifications:

DMX Connectors: 5 Pin XLR Connectors In & Out

(Optional 3-Pin)

Thermal: Max Ambient Temperature 104°

Max Surface Temperature 140°

Fastening System: 6" Dual Yoke

Display: LED

Power Supply: 110V-240 50/60 Hz

Power Consumption: 49 Watts / .65 Amps / .61 PF

Control System:

Protocol: DMX-512

Control Options: Audio Trigger, Main & Remote

Function, Infrared Controller

Channel Modes: **Mode 1** 3 Channels R,G,B

Mode 2 4 Channels R,G,B,W

Mode 3 7 Channels R,G,B,W, Strobe, Macro,

Dimmer

Electrical Specifications:

Power Connection: Power Con Type In and Out

LED Quantity: 7 RGBW
LED Watts: 10W
LED White CCT: 7702K
LED Angle: 16°

Diffusion Beam Angle: 27°

Power Link: 22 Units at 15 Amps @ 110V Ballast: Electronic Auto Switching

Dimensions:

 Fixture Size:
 8.12" x 4.3" x 7.8"

 Fixture Weight:
 5 lb (2.27 kg)

 Packaged Size:
 10" x 9.5" x 5.75"

 Packaged Weight:
 7 lb (3.18 kg)



18662 Bandera Rd Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279 info@mega.lighting