

# STINGER SCAN





## DESCRIPTION

MEGA-LITE has revamped the infamous scanner by creating the Stinger Scan-150, which uses an LED light source. Designed to be more efficient and deliver a high output, this fixture features a 150W single-color LED.

It is packed with the effects you need: eight colors+ open, seven removable bidirectional and indexing rotation gobos, a 4-facet rotatable indexing prism, mechanical focus, 180° pan, and 140° tilt. This fixture can deliver sharp mid-air beams with high-speed movement and yet be an efficient scanner with great slow movements.

When placed against a wall or on the floor, the scanning power fits into areas where other moving head fixtures don't make sense. The fast mirror pace is ideally suited for high-energy music and high-impact lighting, adding excitement to any event.

# Features:



## POWERFUL

Designed to be more powerful and deliver a high output, this fixture features a powerful 150W single color LED.



## EXTREME MOVEMENT

The movement can either be fast and energetic scanning the room with its super fast mirror or deliver precise movement to be focused in a specific area.



## PACKED WITH EFFECTS

The fixture is packed with 8 colors+ open, 7 removable, bi-directional, indexing rotation gobos, and a 4-facet, rotatable, indexing prism.

# Specifications.

## Mechanical Specifications:

Housing:	Seel and plastic
Power connection:	Panel mounted powercon (type) in and out
Signal connection:	Panel mounted 5 PIN XLR connector in and out 3 pin optional)
Pan movement:	180°
Tilt movement:	140°
Colors:	8 Colors + open
Focus:	Mechanical focus
Rotation gobos:	7 Removable, bi-directional, indexing
Prism:	4-Facet, rotatable, indexing
Lens angle:	15°
Fastening system:	Mounting Yoke and can stand on the floor

## Control System:

Control protocols:	DMX 512
RDM:	Yes
Channel modes:	2 Modes of operation: Mode 1: 8 Channel mode Mode 2: 15 Channel mode
Display:	Digital

## Electrical Specifications:

Light source:	150W Single color
Color Temperature:	16403 K
CRI (Warm white):	77
Lumen Output:	5733 lm
Power supply:	Electronic auto switching 100V-240V/50/60Hz
Power consumption:	Watts: 272W   Amps: 2.3A

## Size and Weight:

Fixture size:	10.5" X 6.5" X 18.5"
Fixture weight:	16.5 lb (7.5 kg)
Packaged size:	23.25" X 12" X 20"
Packaged weight:	20 lb (9 kg)



**MEGA** **LITE**®  
WWW.MEGA.LIGHTING

18662 Bandera Rd  
Helotes, TX 78023

Phone (210)684-2600 / Fax (210)855-6279  
info@mega.lighting

m e g a . l i g h t i n g